



DOSIAC

Bombas de vacío

Características y capacidades

Modelo	HP	Desplazamiento l/min			Vacío nominal		RPM		Dimensiones (cm)			Peso Kg	Contenido de aceite (lts)	Conexiones
		50 Hz	60 Hz	CFM	µm Hg	mbar	50 Hz	60 Hz	Ancho	Altura	Largo			
DVR-30	1/8	30	36	1,1	50	0,065	2.890	3.470	12,5	18,0	27,5	7	0,35	1/4" FLARE - 1/2" ACME
DVR-95	1/2	95	114	3,5	15	0,020	1.440	1.730	14,5	26,5	43,0	15	1	1/4" FLARE - 1/2" ACME
DVR-140	1/2	140	170	5	15	0,020	1.440	1.730	14,5	26,5	43,0	15,9	1	1/4" FLARE - 1/2" ACME
DVR-280	1/2	280	340	10	15	0,020	1.425	1.715	14,5	30,0	48,0	21	1,5	1/4" FLARE - 1/2" ACME
DVR II - 1A	1/3	58	71	2	15	0,020	1.425	1.725	11,0	23,0	27,0	7,4	0,25	1/4" FLARE - 1/2" ACME
DVR II - 2A	1/2	130	155	4,5	15	0,020	1.425	1.725	12,0	24,0	32,0	9,4	0,35	1/4" FLARE - 1/2" ACME
DVR-6	1/2	140	170	5	7,5	0,007	1.425	1.715	14,5	26,5	43,0	13,7	1	1/4" - 3/8" - 1/2"
DVR II - 3A	1/2	170	212	6	15	0,020	1.425	1.725	14,0	24,0	35,0	14,6	0,4	1/4" FLARE - 1/2" ACME

Todos los modelos para **110 / 220 V**

Repuestos

N°	TIPO DE PIEZA	MODELO DE BOMBA	CÓDIGO DE PIEZA
1	KIT MODULO DE BOMBEO	DVR 95 DVR 140 DVR 280	R570950-00 R571400-00 R572800-00
2	KIT CARTER	DVR 95 / 140	R570950-07
3	INSERTO MANCHON	DVR 95 / 140 / 280	C331700/6
4	ACOPLAMIENTO	DVR 95 / 140 / 280	C330700/658
5	KIT MANIJA	DVR 95 / 140 DVR 280	R570950-10 R572800-10
6	KIT BASE	DVR 95 / 140 / 280	R570950-08
7	KIT VALVULA	DVR 95 / 140 DVR 280	R570950-10 R572800-01
8	KIT DE JUNTAS	DVR 95 / 140 DVR 280	R570950-05 R572800-05
9	MOTOR	DVR 95 / 140 DVR 280	C0731D/W02 C0721D/W02
10	PANEL DE COMANDO	DVR 30 / 95 / 140 / 280	B57363/00
11	KIT CARTER	DVR 30	R580300-07
12	MANIJA	DVR 30	R580300-10
13	CONEXION T	DVR 30	R580300-01
14	KIT JUNTAS	DVR 30	R580300-05
15	KIT VISOR	DVR 30 / 95 / 140 / 280	57042
		DVR 30	C09062
16	KIT TAPON DE EXPULSION	DVR 95 / 140 DVR 280	57168 B57295

